

Tactic 371+ Programming

1. Press reset button
2. Press "OK"
3. Set hour for current time by pressing (+) or (-) button
4. Press "OK"
5. Set minute current time by pressing (+) or (-) button
6. Press "OK"
7. Set current day (pointer on left must align with current day: Mon = 1)
8. Press "OK"

9. P 01 will appear and 01 will flash
10. Press "OK" button twice

11. **Setting on time**
12. Set hours for first on time using the (+) or (-) buttons. (06:00 is a default time and simply needs altering to first required on time).
13. Press "OK"
14. Set minutes for first on time using the (+) or (-) buttons.
15. Press "OK"
16. Set day or day group for on time using (+) or (-) buttons
17. Press "OK"

18. **Setting off time**
19. Set off time hour using (+) or (-) buttons (22:00 is a default time and simply needs altering to first required on time).
20. Press "OK"
21. Set off time minutes using (+) or (-) buttons
22. Press "OK"
23. Set day or day group for off time using (+) or (-) buttons
24. Press "OK"

To add more on off times repeat the "**Setting on time**" and "**Setting off time**" procedures.
When you have completed adding on/off times and pressed "OK" for the last time, follow steps below.

Press Menu button to return to normal screen with time etc. displayed.